

Type	
Type	Digital interchangeable lens, mirrorless camera
Image Processor	DIGIC X
Recording Media	(Two) SD card slots <ul style="list-style-type: none"> • Compatible with UHS-II • Eye-Fi cards and Multimedia cards (MMC) are not supported.
Compatible Lenses	Canon RF lens group (excluding EF, EF-S and EF-M lenses) When using Mount Adapter EF-EOS R: Canon EF or EF-S lenses (excluding EF-M lenses)
Lens Mount	Canon RF mount
Image Sensor	
Type	CMOS sensor (compatible with Dual Pixel CMOS AF)
Effective Pixels	Approx. 20.1 megapixels
Screen Size	Approx. 36.0 x 24.0 mm
Pixel Unit	Approx. 6.56 μm square
Total Pixels	Approx. 21.4 megapixels
Aspect Ratio	3:2 (Horizontal: Vertical)
Color Filter System	RGB primary color filters
Low Pass Filter	Installed in front of the image sensor, non-detachable
Dust Deletion Feature	<p>(1) Self Cleaning Sensor Unit</p> <ul style="list-style-type: none"> • Removes dust adhering to the low-pass filter. • At power off only / Enable / Disable. Performed automatically (taking about approx. 2 sec. as indicated on the screen) or manually (taking about approx. 8 sec. as indicated on the screen). • After manually activated cleaning, the camera will automatically restart (Power OFF to ON). • When [Multi Shot Noise Reduction], [Multiple exposures], or [HDR mode] is set, [Clean now] and [Clean manually] cannot be selected. <p>(2) Dust Delete Data acquisition and appending</p> <ul style="list-style-type: none"> • The coordinates of the dust adhering to the low-pass filter are detected by a test shot and appended to subsequent images. • The dust coordinate data appended to the image is used by the EOS software to automatically erase the dust spots. • Not available with EF-S lenses, in cropped shooting or multi-exposure shooting. <p>(3) Manual cleaning (by hand)</p>

Recording System

Recording Format

Compliant to Design rule for Camera File system 2.0 and Exif 2.31*.
*Supports time difference information in Exif 2.31.

Image Format

JPEG, HEIF, RAW / C-RAW (CR3), C-RAW (Canon original) ; Movies: ALL-I (Time-lapse video only), IPB, MP4

File Size

	Image Quality	File Size [Approx. MB]	Possible Shots [Approx.]* ¹	Maximum Burst [Approx.]	
				Standard Card * ¹	High-speed Card* ² (UHS-II)
JPEG* ³	L (fine)	7.1	4240	1000 or more	1000 or more
	L (Normal)	3.9	7720	1000 or more	1000 or more
	M (fine)	4.0	7470	1000 or more	1000 or more
	M (Normal)	2.3	12710	1000 or more	1000 or more
	S1 (Fine)	2.8	10860	1000 or more	1000 or more
	S1 (Normal)	1.7	17460	1000 or more	1000 or more
	S2	1.8	16060	1000 or more	1000 or more
HEIF* ⁴	L (fine)	7.5	3940	770	1000 or more
	L (Normal)	5.8	5060	1000 or more	1000 or more
	M (fine)	4.4	6530	1000 or more	1000 or more
	M (Normal)	3.5	8220	1000 or more	1000 or more
	S1 (Fine)	3.0	9330	1000 or more	1000 or more
	S1 (Normal)	2.5	11160	1000 or more	1000 or more
	S2	1.8	14100	1000 or more	1000 or more
RAW	RAW	21.8	1400	110	240
	C-RAW	11.2	2750	240	1000 or more
RAW+JPEG* ³	RAW + L (fine)	21.8+7.1	1050	91	160
	C-RAW + L (fine)	11.2+7.1	1660	140	770
RAW+HEIF* ⁴	RAW + L (fine)	25.0+7.5	940	92	140
	C-RAW + L (fine)	14.3+7.5	1420	140	380

File Numbering	<p>The following file numbers can be set:</p> <ol style="list-style-type: none"> 1. File numbering methods <ol style="list-style-type: none"> a. Continuous numbering <ol style="list-style-type: none"> i. The numbering of captured images continues even after you replace the card. b. Auto reset <ol style="list-style-type: none"> i. When you replace the card, the numbering will be reset to start from 0001. If the new SD card already contains images, the numbering will continue from the last recorded image in the card. 2. Manual reset <ol style="list-style-type: none"> a. Resets the file number to 0001, and creates a new folder automatically. <p>* When manually resetting the file number, folders can also be renamed.</p>
RAW + JPEG / HEIF Simultaneous Recording	Simultaneous recording of any combination of RAW/C-Raw and JPEG/HEIF image-recording quality is supported.
Color Space	Selectable between sRGB and Adobe RGB
Picture Style	<ol style="list-style-type: none"> (1) Auto (2) Standard (3) Portrait (4) Landscape (5) Fine Detail (6) Neutral (7) Faithful (8) Monochrome (9) User Defined 1–3 <ul style="list-style-type: none"> • In Scene Intelligent Auto, [Auto] will be set automatically. • [Standard] is the default setting for [User Def. 1–3].
White Balance	
Settings	<ol style="list-style-type: none"> (1) Auto (Ambience priority/White priority) (2) Daylight (3) Shade (4) Cloudy* (5) Tungsten light (6) White fluorescent light (7) Flash (8) Custom (Custom WB) (9) Color temperature <p>* Effective also in twilight and sunset.</p>
Auto White Balance	Option between ambience priority and white priority settings, using SET button
White Balance Shift	<p>Blue/amber bias: ±9 levels Magenta/green bias: ±9 levels Corrected in reference to the current WB mode's color temperature.</p>
Viewfinder	
Type	OLED color electronic viewfinder
Coverage	Approx. 100% vertically and horizontally relative to the shooting image area (with image quality L, at approx. 23mm eyepoint).
Magnification / Angle of View	Approx. 0.76x / Approx. 35.2 degrees (with 50mm lens at infinity, -1 m ⁻¹)
Eye Point	Approx. 23mm (at -1 m ⁻¹ from the eyepiece lens end)
Dioptic Adjustment Range	Approx. -4.0 to + 2.0 m ⁻¹ (dpt)

Viewfinder Information	<ul style="list-style-type: none"> (1) Maximum burst (2) Possible shots/Sec. until self-timer shoots (3) Focus Bracketing/ Multiple-exposure/HDR shooting/Multi Shot Noise Reduction/Bulb time/Interval timer (4) Shooting mode (5) AF method (6) AF operation (7) Image quality (8) Card (9) Drive mode (10) Metering mode (11) No. of remaining shots for focus bracketing, multiple exposures, or interval timer (12) Electronic level (13) Movie recording time available (14) Battery level (15) Image Stabilizer (IS mode) (16) Histogram (Brightness/RGB) (17) Quick Control button (18) Anti-flicker shooting (19) White balance/White balance correction (20) Picture style (21) Auto Lighting Optimizer (22) Still photo cropping / Aspect ratio (23) AF point (1-point AF) (24) AEB/FEB (25) View Assist (26) HDR PQ (27) Flash ready / FE lock / High-speed sync (28) Electronic shutter (29) Touch shutter / Create folder (30) AE lock (31) Shutter speed / Multi-function lock warning (32) Aperture value (33) Wi-Fi® function (34) Wi-Fi® signal strength (35) Bluetooth® function (36) Exposure simulation (37) Magnify button (38) ISO speed (39) Highlight tone priority (40) Exposure compensation (41) Exposure level indicator
Autofocus	
Focus Method	Dual Pixel CMOS AF
Number of AF zones available for Automatic Selection	AF area: Horizontal: Approx. 100% x Vertical: Approx. 100% (100% x 100% AF coverage in Face Detect + Tracking AF; coverage can vary, depending upon lens being used) Stills: Max. 1053 zones (39 x 27) Movies: Max. 819 zones (39 x 21)
Selectable Positions for AF Point	AF area: Horizontal: Approx. 90% x Vertical: Approx. 100% Stills: Max. 6072 positions (92 x 66) Movies: Max 4968 positions (92 x 54)
AF Working Range	EV -6.5 to 20 (f/1.2 lens*, center AF point, One-Shot AF, at 73°F/23°C, ISO 100) * Except RF lenses with a Defocus Smoothing (DS) coating.

Focusing brightness range (in movie recording)	EV -5 to 20 (f/1.2 lens*, center AF point, One-Shot AF, at 73°F/23°C, ISO 100) * Except RF lenses with a Defocus Smoothing (DS) coating.														
Available AF Methods	<table border="1"> <thead> <tr> <th colspan="2">AF Method</th> </tr> </thead> <tbody> <tr> <td>Face+Tracking AF</td> <td></td> </tr> <tr> <td>Spot AF</td> <td></td> </tr> <tr> <td>1-point AF</td> <td>Must be selected for "Limit AF methods."</td> </tr> <tr> <td>Expand AF Area</td> <td>- 4-point expansion - Around expansion (8-points)</td> </tr> <tr> <td>Zone AF</td> <td></td> </tr> <tr> <td>Large Zone AF: Vertical, Horizontal</td> <td></td> </tr> </tbody> </table>	AF Method		Face+Tracking AF		Spot AF		1-point AF	Must be selected for "Limit AF methods."	Expand AF Area	- 4-point expansion - Around expansion (8-points)	Zone AF		Large Zone AF: Vertical, Horizontal	
AF Method															
Face+Tracking AF															
Spot AF															
1-point AF	Must be selected for "Limit AF methods."														
Expand AF Area	- 4-point expansion - Around expansion (8-points)														
Zone AF															
Large Zone AF: Vertical, Horizontal															
Available AF Detection zones	<table border="1"> <tbody> <tr> <td>Zone AF</td> <td>9 x 9</td> </tr> <tr> <td>Large Zone AF: Vertical</td> <td>Max. 9 x 21</td> </tr> <tr> <td>Large Zone AF: Horizontal</td> <td>Max. 31 x 9</td> </tr> <tr> <td>Face+Tracking (Auto selection with nothing detected)</td> <td>Max. 39 x 27</td> </tr> </tbody> </table>	Zone AF	9 x 9	Large Zone AF: Vertical	Max. 9 x 21	Large Zone AF: Horizontal	Max. 31 x 9	Face+Tracking (Auto selection with nothing detected)	Max. 39 x 27						
Zone AF	9 x 9														
Large Zone AF: Vertical	Max. 9 x 21														
Large Zone AF: Horizontal	Max. 31 x 9														
Face+Tracking (Auto selection with nothing detected)	Max. 39 x 27														
Eye Detection	<p>Auto:</p> <ol style="list-style-type: none"> 1. Selects the eye closer to the camera (as detected from the angle of the face). 2. At the same distance from the camera, selects the eye closer to the center of the image. <p>Manual:</p> <ol style="list-style-type: none"> 1. Can be selected by touch. 2. Can be selected with the Multi-controller. 														
Exposure Control															
Metering Modes	Real-time metering with image sensor (384 [24x16] metering zones) (1) Evaluative metering (AF point-linked) (2) Partial metering (approx. 5.8% of the area at the center of the screen) (3) Spot metering (approx. 2.9% of the area at the center of the screen) (4) Center-weighted average metering														
Metering Range	EV -3 – 20 (at 73°F/23°C, ISO 100) (Still Photo Shooting)														
Exposure Modes	<ol style="list-style-type: none"> (1) Scene Intelligent Auto (2) Flexible-priority AE (Fv) (3) Program AE (P) (4) Shutter-priority AE (Safety shift possible) (Tv) (5) Aperture-priority AE (Safety shift possible) (Av) (6) Manual exposure (M) (7) Bulb (8) Custom shooting mode C1, C2, C3 														

ISO Speed Range	Manually Set															
	<table border="1"> <tr> <td>Normal</td> <td>ISO 100–102400 (in 1/3- or 1-stop increments)</td> </tr> <tr> <td>Expanded</td> <td>L: equivalent to ISO 50, H: 204800</td> </tr> </table> <ul style="list-style-type: none"> • For [Highlight tone priority], the settable ISO speed range will be ISO 200 to 102400. • Expanded ISO cannot be set for HDR mode or during HDR PQ shooting. 	Normal	ISO 100–102400 (in 1/3- or 1-stop increments)	Expanded	L: equivalent to ISO 50, H: 204800											
	Normal	ISO 100–102400 (in 1/3- or 1-stop increments)														
	Expanded	L: equivalent to ISO 50, H: 204800														
ISO Auto range settings in still photo shooting																
<table border="1"> <tr> <td></td> <td>Auto Range</td> </tr> <tr> <td>ISO Speed</td> <td>ISO 100-102400</td> </tr> </table> <p>* 1-stops increments</p>		Auto Range	ISO Speed	ISO 100-102400												
	Auto Range															
ISO Speed	ISO 100-102400															
	ISO Auto details in still photo shooting															
	<table border="1"> <thead> <tr> <th>Shooting mode</th> <th>No Flash</th> <th>Using Flash</th> </tr> </thead> <tbody> <tr> <td>Auto</td> <td>ISO 100-25600</td> <td>ISO 100-6400*4</td> </tr> <tr> <td>P</td> <td rowspan="4">ISO 100*1*2-102400*2</td> <td rowspan="4">ISO 100*1*2-6400*2*4</td> </tr> <tr> <td>TV</td> </tr> <tr> <td>AV</td> </tr> <tr> <td>M</td> </tr> <tr> <td>B</td> <td colspan="2">ISO 400*3</td> </tr> </tbody> </table> <p>* 1: ISO 200 when [Highlight tone priority] is set to [Enable] or [Enhanced]. * 2: Varies depending on [Maximum] and [Minimum] of [Auto range]. * 3: If outside the setting range, changed to the value most close to ISO 400. * 4: ISO 1600 when using a lens that is not compatible with "Variable control of maximum ISO Auto limit for E-TTL".</p>	Shooting mode	No Flash	Using Flash	Auto	ISO 100-25600	ISO 100-6400*4	P	ISO 100*1*2-102400*2	ISO 100*1*2-6400*2*4	TV	AV	M	B	ISO 400*3	
Shooting mode	No Flash	Using Flash														
Auto	ISO 100-25600	ISO 100-6400*4														
P	ISO 100*1*2-102400*2	ISO 100*1*2-6400*2*4														
TV																
AV																
M																
B	ISO 400*3															
Exposure Compensation	<table border="1"> <tr> <td>User-set</td> <td>±3 stops in 1/3- or 1/2-stop increments</td> </tr> <tr> <td>AEB</td> <td>±3 stops in 1/3- or 1/2-stop increments</td> </tr> </table>	User-set	±3 stops in 1/3- or 1/2-stop increments	AEB	±3 stops in 1/3- or 1/2-stop increments											
User-set	±3 stops in 1/3- or 1/2-stop increments															
AEB	±3 stops in 1/3- or 1/2-stop increments															
AE Lock	<p>(1) Auto AE lock</p> <ul style="list-style-type: none"> • The metering mode for AE lock after focus can be customized. <p>(2) User-set AE lock</p> <ul style="list-style-type: none"> • In the Fv, P, Tv, Av and M modes, enabled with the AE lock button. (Press again to update.) • Enabled in all metering modes. 															
Shutter																
Type	<p>Electronically controlled focal-plane shutter</p> <p>(1) Electronic first curtain (2) Mechanical shutter (3) Electronic shutter*</p> <p>* Cannot be used in conjunction with the following functions: flash photography, HDR shooting, multiple exposures, Multi Shot Noise Reduction, AEB, HDR PQ, anti-flicker shooting, Dual Pixel RAW shooting, Digital Lens Optimizer [High].</p> <p>* A shutter release sound is not generated. However, note that the sounds other than the shutter release sound (aperture, focusing lens drive sound/electronic sound, etc.) may be generated.</p> <p>* In electronic shutter shooting under conditions such as flash firing by other cameras or with fluorescent lighting or other flickering light sources, a strip of light or banding due to the brightness difference may be recorded in the image.</p>															
Shutter Speeds	<p>When [Mechanical] or [Elec. 1st- curtain] is set: 1/8000-30 sec, bulb</p> <p>When [Electronic] is set: 1/8000-0.5 sec.</p>															
X-sync Speed	<p>Mechanical Shutter: 1/200 sec.</p> <p>Elec. 1st-curtain: 1/250 sec.</p>															
Shutter Release	Soft-touch electromagnetic release															

Self Timer	10-sec. delay, 2-sec. delay																																														
Image Stabilization (IS mode)																																															
Still Photo IS	In-body IS operation can be selected when using a non-IS lens. <ul style="list-style-type: none"> • Always on • Only for shot (no stabilization in viewfinder/LCD screen between shots) 																																														
External Speedlite																																															
E-TTL balance	Ambience priority, standard, flash priority																																														
Flash Exposure Compensation	±3 stops in 1/3- or 1/2-stop increments																																														
Continuous flash control	1. E-TTL each shot 2. E-TTL locked after first shot in sequence																																														
Drive System																																															
Drive Modes and Continuous Shooting Speed	<table border="1"> <thead> <tr> <th>Drive Modes</th> <th>Operating Modes</th> <th>Mechanical Shutter</th> <th>Electronic 1st curtain</th> <th>Electronic shutter</th> </tr> </thead> <tbody> <tr> <td colspan="2">Single Shooting</td> <td>Yes</td> <td>Yes</td> <td>Yes</td> </tr> <tr> <td rowspan="3">High-speed Continuous + Shooting*1</td> <td>Mode A*2</td> <td colspan="3">Approx. 12 shots/sec.</td> </tr> <tr> <td>Mode B</td> <td colspan="3">Approx. 9.2 shots/sec.</td> </tr> <tr> <td>Mode C</td> <td colspan="3">Approx. 6.8 shots/sec.</td> </tr> <tr> <td rowspan="3">High-speed Continuous shooting</td> <td>Mode A*2</td> <td>Approx. 6.0 shots/sec.</td> <td>Approx. 8.0 shots/sec.</td> <td rowspan="6">Approx. 20 shots/sec</td> </tr> <tr> <td>Mode B</td> <td>Approx. 5.1 shots/sec.</td> <td>Approx. 6.0 shots/sec.</td> </tr> <tr> <td>Mode C</td> <td>Approx. 3.8 shots/sec.</td> <td>Approx. 4.9 shots/sec.</td> </tr> <tr> <td colspan="2">Low-speed Continuous Shooting</td> <td colspan="2">Approx. 3.0 shots/sec.</td> </tr> <tr> <td colspan="2">Self-timer:10 sec / remote control</td> <td colspan="2">Yes</td> </tr> <tr> <td colspan="2">Self-timer:2 sec / remote control</td> <td colspan="2">Yes</td> </tr> </tbody> </table>	Drive Modes	Operating Modes	Mechanical Shutter	Electronic 1st curtain	Electronic shutter	Single Shooting		Yes	Yes	Yes	High-speed Continuous + Shooting*1	Mode A*2	Approx. 12 shots/sec.			Mode B	Approx. 9.2 shots/sec.			Mode C	Approx. 6.8 shots/sec.			High-speed Continuous shooting	Mode A*2	Approx. 6.0 shots/sec.	Approx. 8.0 shots/sec.	Approx. 20 shots/sec	Mode B	Approx. 5.1 shots/sec.	Approx. 6.0 shots/sec.	Mode C	Approx. 3.8 shots/sec.	Approx. 4.9 shots/sec.	Low-speed Continuous Shooting		Approx. 3.0 shots/sec.		Self-timer:10 sec / remote control		Yes		Self-timer:2 sec / remote control		Yes	
	Drive Modes	Operating Modes	Mechanical Shutter	Electronic 1st curtain	Electronic shutter																																										
	Single Shooting		Yes	Yes	Yes																																										
	High-speed Continuous + Shooting*1	Mode A*2	Approx. 12 shots/sec.																																												
		Mode B	Approx. 9.2 shots/sec.																																												
		Mode C	Approx. 6.8 shots/sec.																																												
	High-speed Continuous shooting	Mode A*2	Approx. 6.0 shots/sec.	Approx. 8.0 shots/sec.	Approx. 20 shots/sec																																										
		Mode B	Approx. 5.1 shots/sec.	Approx. 6.0 shots/sec.																																											
		Mode C	Approx. 3.8 shots/sec.	Approx. 4.9 shots/sec.																																											
	Low-speed Continuous Shooting		Approx. 3.0 shots/sec.																																												
Self-timer:10 sec / remote control		Yes																																													
Self-timer:2 sec / remote control		Yes																																													
<p>1. Continuous shooting speed is lower under certain shooting and measurement conditions: shutter speed, aperture value subject conditions, brightness, type of lens, timing when internal memory becomes full (temporarily disables shooting)</p> <p>- Mechanical / electronic 1st curtain: use of flash, anti-flicker shooting: Enable, Dual Pixel RAW shooting- Enable, type of battery, battery level, temperature, use of a battery grip, use of WFT, use of built-in Wi-Fi.</p> <p>- Electronic shutter: State of aperture in continuous shooting</p> <p>* With Certain lenses, zooming during continuous shooting with electronic shutter may cause changes in exposure even at the same f/number.</p> <p>2. Automatically switches among modes A (drive mode icon lit in green), B (drive mode icon lit in white), and C (drive mode icon flashing in white).</p> <p>* For flash shooting, values for AE, flash metering, and WB do not change after the first shot.</p>																																															
HDR Shooting																																															
HDR Shooting (HDR PQ)	Disable / Enable																																														
Still Photo HDR PQ	<table border="1"> <thead> <tr> <th>Recording format</th> <th>Bit depth</th> <th>Color sampling method</th> <th>HDR specification</th> </tr> </thead> <tbody> <tr> <td>HEIF</td> <td>10 bit</td> <td>YCbCr 4:2:2</td> <td>ITU-R BT.2100 (PQ)</td> </tr> </tbody> </table>	Recording format	Bit depth	Color sampling method	HDR specification	HEIF	10 bit	YCbCr 4:2:2	ITU-R BT.2100 (PQ)																																						
Recording format	Bit depth	Color sampling method	HDR specification																																												
HEIF	10 bit	YCbCr 4:2:2	ITU-R BT.2100 (PQ)																																												
Movie HDR PQ	<table border="1"> <thead> <tr> <th>Recording format</th> <th>Bit depth</th> <th>Color sampling method</th> <th>HDR specification</th> </tr> </thead> <tbody> <tr> <td>mp4</td> <td>10 bit</td> <td>YCbCr 4:2:2</td> <td>ITU-R BT.2100 (PQ)</td> </tr> </tbody> </table>	Recording format	Bit depth	Color sampling method	HDR specification	mp4	10 bit	YCbCr 4:2:2	ITU-R BT.2100 (PQ)																																						
Recording format	Bit depth	Color sampling method	HDR specification																																												
mp4	10 bit	YCbCr 4:2:2	ITU-R BT.2100 (PQ)																																												
Continuous HDR Shooting (still images)	<p>(1) 1 shot only (3 shots taken, one finished HDR image produced in-camera — camera then reverts to normal shooting)</p> <p>(2) Continuously (HDR mode remains active, after first finished HDR image is produced in-camera)</p>																																														

Video Shooting

Shooting Times

Resolution and Frame Rate	Mode	Approx. shooting time (23°C / 73°F)* ¹	Recommended scene
4K 60p	94% sensor width (5.1K oversampling)	30 min	Independent films shooting action or with the option of slow motion at high resolution.
	APS-C Crop	35 min* ³	Independent films shooting action at high resolution with the need for additional reach for sports or wildlife or tighter crops.
4K 30p	94% sensor width (5.1K oversampling)	40 min* ³	General purpose

*¹ Time available for continuous shooting in 23°C / 73°F environment, from a cold start. If the camera is in LV mode standby before shooting or the ambient temperature is high, the shooting time may be shorter.

*² Recording stops at 7minutes and 30seconds for high frame rate video. Indicates the time when recording can be resumed immediately.

*³ Recording is limited to 29 minutes 59 seconds. Indicates the time when recording can be resumed immediately.

Estimated Camera Recovery Time

Estimated recovery times are indicated below. These are affected by various factors such as ambient temperature, continued camera operation and the selected shooting resolution. The time until full record time is available will vary with ambient temperature.

Resolution and Frame Rate	Waiting period (minutes) (23°C / 73°F)	Approximate maximum recording time after waiting period (minutes)
4K 60p	10	5

File Format

Normal Movies

	Canon Log		
	OFF	ON	ON
HDR PQ	OFF	ON	OFF
Container format	MP4		
Bit depth	8 bit	10 bit	
Compression	H.264 / MPEG-4 AVC	H.265 / HEVC	
Video signal recording range	Full range (0-255)	Full range (0-1023)	Full range (128-1016)
Color sampling method	YCbCr 4:2:0	YCbCr 4:2:2	
Color Matrix	Rec.ITU-R BT.709	Rec.ITU-R BT.2020	Rec.ITU-R BT.709/ BT.2020
Audio	IPB	AAC / Linear PCM*	
	IPB (light)	AAC	

* Selection of AAC and Linear PCM is supported [C.Fn 4-2: Audio compression]

Estimated Recording time, Movie Bit Rate and File Size

H.264/AVC (Canon Log: Off, HDR PQ: Off)

Video Recording Size			Total Recording Time (approx.)			Bit Rate/File Size (approx.)
			64 GB	256 GB	1 TB	
4K UHD	59.94 fps	IPB (Standard)	4 min.	18 min.	1 hr. 13 min.	230 Mbps 1656 MB/min.
		IPB (Light)	8 min.	35 min.	2 hr. 21 min.	120 Mbps 860 MB/min.
	29.97 fps 23.98 fps	IPB (Standard)	8 min.	35 min.	2 hr. 20 min.	120 Mbps 869 MB/min.
		IPB (Light)	17 min.	1 hr.10 min.	4 hr. 43 min.	60 Mbps 431 MB/min.
4K UHD (Time-lapse movie)	29.97 fps	ALL-I	2 min.	9 min.	36 min.	470 Mbps 3362 MB/min.
Full UHD (High Frame Rate movie)	119.88 fps [^]	IPB (Standard)	8 min.	35 min.	2 hr. 22 min.	120 Mbps 858 MB/min
		IPB (Light)	15 min.	1 hr. 0 min.	4 hr. 3 min.	70 Mbps 501 MB/min
Full HD	59.94 fps	IPB (Standard)	17 min.	1 hr. 9 min.	4 hr. 37 min.	60 Mbps 440 MB/min.
		IPB (Light)	30 min.	2 hr. 0 min.	8 hr. 3 min.	35 Mbps 252 MB/min.
	29.97 fps 23.98 fps	IPB (Standard)	33 min.	2 hr. 15 min.	9 hr. 1 min.	30 Mbps 226 MB/min.
		IPB (Light)	1 hr. 18 min.	5 hr. 15 min.	21 hr. 0 min.	12 Mbps 97 MB/min.
Full HD (Time-lapse movie)	29.97 fps	ALL-I	11 min.	47 min.	3 hr. 9 min.	90 Mbps 644 MB/min.
Full HD (HDR movie)	29.97 fps	IPB (Standard)	33 min.	2 hr. 15 min.	9 hr. 1 min.	30 Mbps 226 MB/min.

[^] Full-HD 119.88p [High Frame Rate] is not possible with the use of the [Movie Cropping] function. Additionally, the use of an EF-S lens with an EF-EOS R Mount Adapter causes the [Movie Cropping] function to automatically be set to [Enable], and Full-HD 119.88p [High Frame Rate] will not be possible.

H.265/HEVC (Canon Log: On or HDR PQ: On)

Video Recording Size			Total Recording Time (approx.)			Bit Rate/File Size (approx.)
			64 GB	256 GB	1 TB	
4K UHD	59.94 fps	IPB (Standard)	3 min.	12 min.	49 min.	340 Mbps 2443 MB/min.
		IPB (Light)	6 min.	25 min.	1 hr. 40 min.	170 Mbps 1218 MB/min.
	29.97 fps 23.98 fps	IPB (Standard)	6 min.	24 min.	1 hr. 39 min.	170 Mbps 1227 MB/min.
		IPB (Light)	12 min.	50 min.	3 hr. 20 min.	85 Mbps 610 MB/min.
4K UHD (Time-lapse movie)	29.97 fps	ALL-I	2 min.	9 min.	36 min.	470 Mbps 3362 MB/min.
Full HD (High Frame Rate movie)	119.88 fps [^]	IPB (Standard)	5 min.	23 min.	1 hr. 34 min.	180 Mbps 1287 MB/min.
		IPB (Light)	10 min.	42 min.	2 hr. 50 min.	100 Mbps 715 MB/min.
Full HD	59.94 fps	IPB (Standard)	11 min.	46 min.	3 hr. 6 min.	90 Mbps 655 MB/min.
		IPB (Light)	21 min.	1 hr. 24 min.	5 hr. 39 min.	50 Mbps 360 MB/min.
	29.97 fps 23.98 fps	IPB (Standard)	22 min.	1 hr. 31 min.	6 hr. 6 min.	45 Mbps 333 MB/min.
		IPB (Light)	37 min.	2 hr. 30 min.	10 hr. 3 min.	28 Mbps 202 MB/min.
Full HD (Time-lapse movie)	29.97 fps	ALL-I	7 min.	31 min.	2 hr. 6 min.	135 Mbps 966 MB/min.

Estimated Recording Time, Continued.

* Bit rate indicates video output only, audio is not included.

* Movie recording is interrupted if the maximum recording time per movie, 29 min. 59 sec., is exceeded. (Time is different for High Frame Rate movies.)

* Sound is not recorded for approx. the last two frames when the compression method for movie recording quality is IPB or IPB Light (audio: AAC) or [Audio compression] is set to [Enable].

* The video and sound may be slightly out of sync when movies are played back in Windows.

[^] Full-HD 119.88p [High Frame Rate] is not possible with the use of the [Movie Cropping] function. Additionally, the use of an EF-S lens with an EF-EOS R Mount Adapter causes the [Movie Cropping] function to automatically be set to [Enable], and Full-HD 119.88p [High Frame Rate] will not be possible.

	Movie Recording Size			SD Card		
	Resolution	Frame rate (fps)	Compression Method	H.264/ MPEG-4 AVC (Canon Log: OFF, HDR PQ: OFF)	H.264/ MPEG-4 AVC (Canon Log: ON, HDR PQ: ON)	
Card Performance Requirements	4K UHD	59.94	IPB (Standard)	UHS-I, UHS Speed Class 3 or higher	UHS-II, Video Speed Class 60 or higher	
		29.97 23.98	IPB (Standard)	UHS-I, UHS Speed Class 3 or higher		
	Full HD	119.88[^]	IPB (Standard)			SD Speed Class 10 or higher
		59.94	IPB (Standard)	UHS-I, UHS Speed Class 3 or higher		
		29.97 23.98	IPB (Standard)	SD Speed Class 6 or higher		
		29.97	IPB (Light)	SD Speed Class 4 or higher		
	4K UHD (Time-lapse movie)	29.97	ALL-I	Read speed of 60 MB/s or higher		
	Full HD (Time-lapse movie)	29.97	ALL-I	Read speed of 30 MB/s or higher		
	<p>* When cropped movie recording and Movie digital IS are disabled. [^] Full-HD 119.88p [High Frame Rate] is not possible with the use of the [Movie Cropping] function. Additionally, the use of an EF-S lens with an EF-EOS R Mount Adapter causes the [Movie Cropping] function to automatically be set to [Enable], and Full-HD 119.88p [High Frame Rate] will not be possible.</p>					
	Video AF	Dual Pixel CMOS AF; Movie Servo AF available in AF Menu				
Exposure Compensation	±3 stops in 1/3- or 1/2-stop increments					
LCD Screen						
Type	TFT color, liquid-crystal monitor					
Monitor Size	3.0-inch (screen aspect ratio of 3:2) 2.95 in./7.5cm diagonal (2.44 in./6.2cm width, 1.65 in./4.2cm height)					
Dots	Approx. 1.62 million dots					
Coverage	Approx. 100% vertically/horizontally					
Brightness Control	Manually adjustable to one of seven brightness levels					
Touch-screen Operation	Supported for AF Point selection; Touch AF; Touch Shutter; Menu selection; Quick Control Menu; Magnified view					
Coating	Clear View LCD II <ul style="list-style-type: none"> • Anti-smudge coating applied. • Anti-reflection coating not applied. 					

Interface Languages	29 (English, German, French, Dutch, Danish, Portuguese, Finnish, Italian, Ukraine, Norwegian, Swedish, Spanish, Greek, Russian, Polish, Czech, Hungarian, Vietnamese, Hindi, Romanian, Turkish, Arabic, Thai, Simplified/Traditional Chinese, Korean, Malay, Indonesian, Japanese)		
Playback			
Display Format	Item	Still Photo	Movie
	Magnify zoom display	1.5x–10x (15 levels)	-
	AF point display	Yes	-
	Grid display	Off / 3×3 / 6×4 / 3×3+diag	-
	Rating	OFF / 1 to 5 Stars Select images / Select range / All images in folder / All images on card / All found images	
	Image Search	Search conditions Rating / Date / Folder / Protect / Type of file	
	Protect	Select images / Select range / All images in folder / Unprotect all images in folder / All images on card / Unprotect all images on card / All found images	
	Shooting information display	No information display / Basic information display / Detailed shooting information display	
Highlight Alert	The white areas with no image data will blink.		
Histogram	Brightness and RGB		
Quick Control Function			
Function	The Quick Control screen is accessed by pressing the Quick Control button during still photo shooting.		
Image Protection and Erase			
Protection	(1) Single image (select image) (2) Select range (3) All images in a folder (4) All images on card <ul style="list-style-type: none"> • Image browsing and image search can be based on ratings. • Ratings-based image selections also possible with DPP. (5) All found images (only during image search)		
Erase	Except protected images (1) Select images to erase (2) Select range (3) All images in folder (4) All images on card (5) All found images (only during image search)		
Direct Printing			
Compatible Printers	Not supported		
DPOF: Digital Print Order Format			
DPOF	Compliant to DPOF Version 1.1		
Wi-Fi®			
Standards Compliance	IEEE 802.11b/g/n		
Transmission Method	DS-SS modulation (IEEE 802.11b) OFDM modulation (IEEE 802.11g/n)		

Transition Frequency (Central Frequency)	2.4 GHz band (5 GHz Wi-Fi not supported) Frequency: 2412 to 2462 MHz Channels: 1 to 11 channels			
Connection Method	(1) Camera access point mode (2) Infrastructure mode			
Security	Connection Method	Authentication	Encryption	
			Encryption	Key Format and Length
	Camera Access Point	WPA2-PSK	AES	• ASCII 8 characters
		Open	Disable	
	Infrastructure	Open	WEP	• Hexadecimal 10 digits • Hexadecimal 26 digits • ASCII 5 characters • ASCII 13 characters
			Disable	
		Shared key	WEP	Same as WEP above
		WPA-PSK	TKIP	• Hexadecimal 64 digits
	WPA2-PSK	AES	• ASCII 8–63 characters	
Communication with a Smartphone	Images can be viewed, controlled, and received using a smartphone. Remote control of the camera using a smartphone is possible depending on the Camera Connect specifications. Images can be sent to a smartphone.			
Remote Operation Using EOS Utility	The camera can be controlled via Wi-Fi®, with Canon EOS Utility software installed in a compatible Mac or Windows computer.			
Print from Wi-Fi® Printers	Not supported.			
Send Images to a Web Service	image.canon: Video files (MP4) and JPEG, HEIF, RAW or C-Raw still images can be uploaded to image.canon servers. From image.canon, images can be sent to specific social media and 3rd-party cloud image services.			
Bluetooth®				
Standards Compliance	Bluetooth Specification Version 4.2 compliant (Bluetooth low energy technology)			
Transmission Method	GFSK modulation			
Customization				
Available Functions	Dial direction during Tv/Av; Control ring rotation direction; Customize buttons; Customize dials			

<p>Custom Controls</p>	<p>Customizable Buttons</p> <table border="1" data-bbox="456 163 976 573"> <tr><td>Shutter button</td></tr> <tr><td>Movie button</td></tr> <tr><td>MODE button</td></tr> <tr><td>AF-ON button</td></tr> <tr><td>AE lock button</td></tr> <tr><td>AF point button</td></tr> <tr><td>Depth of field preview button</td></tr> <tr><td>Lens AF stop button</td></tr> <tr><td>Multi-function button</td></tr> <tr><td>LCD panel illumination button</td></tr> <tr><td>Set button</td></tr> <tr><td>Multi-controller</td></tr> </table>	Shutter button	Movie button	MODE button	AF-ON button	AE lock button	AF point button	Depth of field preview button	Lens AF stop button	Multi-function button	LCD panel illumination button	Set button	Multi-controller
Shutter button													
Movie button													
MODE button													
AF-ON button													
AE lock button													
AF point button													
Depth of field preview button													
Lens AF stop button													
Multi-function button													
LCD panel illumination button													
Set button													
Multi-controller													
<p>Customizable Dials</p>	<table border="1" data-bbox="456 604 976 709"> <tr><td>Main dial</td></tr> <tr><td>Quick control dial 1 & 2</td></tr> <tr><td>Control ring</td></tr> </table>	Main dial	Quick control dial 1 & 2	Control ring									
Main dial													
Quick control dial 1 & 2													
Control ring													
<p>My Menu Registration</p>	<ul style="list-style-type: none"> • Up to six top-tier menu items and Custom Functions can be registered. • Up to five My Menu tabs can be added. <table border="1" data-bbox="472 827 1260 1115"> <tr> <td data-bbox="472 827 818 947"> <p>My Menu tab overall operations</p> </td> <td data-bbox="818 827 1260 947"> <ul style="list-style-type: none"> • Adding a tab • Deleting tabs in a batch • Deleting all tab items • Setting the menu display </td> </tr> <tr> <td data-bbox="472 947 818 1115"> <p>My Menu tab detailed operations</p> </td> <td data-bbox="818 947 1260 1115"> <ul style="list-style-type: none"> • Selecting a registered item • Sorting registered items • Deleting selected registered items • Deleting registered items in a batch • Deleting tabs • Changing a tab name (16 ASCII characters) </td> </tr> </table>	<p>My Menu tab overall operations</p>	<ul style="list-style-type: none"> • Adding a tab • Deleting tabs in a batch • Deleting all tab items • Setting the menu display 	<p>My Menu tab detailed operations</p>	<ul style="list-style-type: none"> • Selecting a registered item • Sorting registered items • Deleting selected registered items • Deleting registered items in a batch • Deleting tabs • Changing a tab name (16 ASCII characters) 								
<p>My Menu tab overall operations</p>	<ul style="list-style-type: none"> • Adding a tab • Deleting tabs in a batch • Deleting all tab items • Setting the menu display 												
<p>My Menu tab detailed operations</p>	<ul style="list-style-type: none"> • Selecting a registered item • Sorting registered items • Deleting selected registered items • Deleting registered items in a batch • Deleting tabs • Changing a tab name (16 ASCII characters) 												
<p>Interface</p>													
<p>USB Terminal</p>	<p>Equivalent to Hi-Speed USB (USB 3.1 Gen 2)</p> <ul style="list-style-type: none"> • For PC communication • Terminal type: USB Type-C • Shared with terminal for in-camera charging with USB Power Adapter PD-E1. • In-camera Charging: Equivalent to USB type-C (5 V/1.5 A), but use should be restricted to USB Power Adapter PD-E1. 												
<p>HDMI Out Terminal</p>	<p>HDMI micro OUT terminal Type D (Resolution switches automatically) / CEC not compatible</p> <ul style="list-style-type: none"> • Images can be displayed through the HDMI output and on screen at the same time. • Images will not be displayed unless [NTSC] or [PAL] is properly set according to the video system of the TV set. 												
<p>Clean HDMI Output</p>	<p>Provided</p>												
<p>Microphone terminal</p>	<p>3.5mm diameter stereo mini jack</p>												

Headphone terminal	Compatible with 3.5mm diameter stereo mini-plug
Power Source	
Battery	<p>Canon LP-E6NH battery pack (also compatible with LP-E6N and LP-E6 battery packs)</p> <ul style="list-style-type: none"> • With the AC Adapter AC-E6N + DC Coupler DR-E6, AC power is possible. • With the USB Power Adapter PD-E1, in-camera charging of LP-E6NH is possible. The USB Power Adapter PD-E1 is not compatible with powering the camera.
Optional Battery Grip	<p>Compatible with Canon Battery Grip BG-R10 (Accepts one or two LP-E6NH, LP-E6N, or LP-E6 battery packs)</p>
Battery Check	<p>Automatic battery check when the power switch is turned ON. Displayed in 5 levels in viewfinder, and on LCD screen.</p> <p>Battery info display in Set-up Menu:</p> <ul style="list-style-type: none"> • Remaining capacity percentage • Shutter count, on current battery charge • Recharge performance (battery's ability to hold charge; displayed in 3 levels)
Start-up Time	<p>Approx. 0.4 sec.</p> <ul style="list-style-type: none"> • Based on CIPA testing standards.
Dimensions and Weight	
Dimensions (W x H x D)	<p>Approx. 5.45 x 3.84 x 3.48 in. / 138 x 97.5 x 88.4mm</p> <ul style="list-style-type: none"> • Based on CIPA standards.
Weight	<p>Approx. 1.5 lbs. / 680g (including battery, SD memory card; without body cap) Approx. 1.3 lbs. / 598g (body only; without battery, card or body cap)</p>
Operating Environment	
Working Temperature Range	32–104°F / 0–+40°C
Working Humidity Range	85% or less